Selection Guide and Optional Parts

Name Plate

GD35	<u>5R5G</u>	4	<u>2 T</u>	* *
1	2	3	4 5	6

Sign	Description of the sign	Specific Contents
1	Abbreviation	Goodrive35: Spindle positioning series frequency inverter
2	Power Range + Load Type	5R5-5.5kW G — constant torque load
3	Voltage	4:3-phase 380V~440V
4	IP Class	Protection class (standard product defaulted): 0-IP00; 1-IP20; 2-IP21; 3-IP31; 5-IP54; 6-IP65;
5	Synchronous Motor Mark	T: synchronous motor; asynchronous motor defaulted
6	Type of PG Card	 A1: 5V differential increment encoder B1: 12V differential increment encoder C1: 24V differential increment encoder D1: Resolver H1: 5V/12V differential increment encoder, with pulse/position differential input

Power Ratings

Model No.	Output Power (kW)	Input Current(A)	Output Current (A)	Carrier Frequency (kHz)
GD35-1R5G-4	1.5	5.0	3.7	2~15(8)
GD35-2R2G-4	2.2	5.8	5.0	2~15(8)
GD35-004G-4	4	13.5	9.5	2~15(8)
GD35-5R5G-4	5.5	19.5	14	2~15(8)
GD35-7R5G-4	7.5	25	18.5	2~15(8)
GD35-011G-4	11	32	25	2~15(8)
GD35-015G-4	15	40	32	2~8(4)
Big power section	18. 5~75	Determined by rated power	Determined by rated power	2~8(4)

Notes

 The identification of types of big power section is similar and the power range varies from 18.5kW to 75kW.
 Installation dimensions of various types are identical to that of Goodrive 300 frequency inverter of the corresponding power grade.

Keypad, communication function and extension card		
High Performance Keypad	Identical to that of Goodrive300	
Three kinds of communication interface	1. Built-in modbus interface; 2. Two-in-one extension card: Profilebus-DP bus plus Ethernet	

invt

Electric Power:

SHENZHEN INVT ELECTRIC CO., LTD. Industrial Automation : Frequency Inverter Servo & HMI

SVG

Intelligent Solar Inve

INVT Copyright. Information may be subject to change without notice during product im

 \oplus

 \oplus

Goodrive35

Close Loop Vector Control Inverter



Your trusted industry automation solution provider



Service line:86-755-23535967 E-mail:overseas@invt.com.cn Website:www.invt.com

INVT Guangming Technology Building, Songbai Road, Matian, Guangming District, Shenzhen, China

& Motion Control	Motor & Electric Spind	lle PLC	
ent Elevator Control System	Traction Drive		
verter	UPS	Online Energy Mar	nagement System
improving.		66003-00069	Y8/1-11(V2.1)











Goodrive35 Product Profile

The Goodrive35 Series Close Loop Vector Control Inverter is developed from the Goodrive300.It is a more accurate and powerful closed-loop vector frequency inverter

Characteristics and Applications

- High performance closed-loop vector control
- High accuracy position control
- Applicable for CNC machine, woodworking machine and non-woven fabrics machine etc.
- Applicable for other industrial applications required for high performance closed-loop vector control

Product Features

Compatible with Multiple Motors

(1) It can drive variety of motors: high-speed motor, electric spindle, variable frequency motor, AC servo motor, various synchronous motor and ordinary asynchronous motor







More Accurate Motor Autotuning

Correct rotating and static motor autotuning. Convenient debugging,easy operation.

Rotating Autotuning	Static Autotuning
De-couple from the load	No need to de-couple from the load
Applied to the situation with high control accuracy	Applied when rotating autotuning is not available

Closed-loop Vector Control

More accurate and powerful torque control, speed control and position control

(1) Position control applicable for machine positioning

Characteristics	Goodrive35
Position control precision	\pm 1 pulse

(2) Torque and speed control performance ensure the motor runs stably and responds rapidly with small torque fluctuation

Features	Goodrive35
Speed Ratio	1:1000
Speed Accuracy	\pm 0.02%
Torque Response	<10ms
Torque Control Accuracy	5%
Starting Frequency Starting Torque	0Hz/200%

(3) Excellent weak magnetic control capacity to meet the requirements on rapid acceleration and deceleration.

TÜV SÜD Product Certification



Special function for machine tools

Functions	Descripti
Frequency Setting	Analog: 0 communic
Exact Stopping of Spindle	Built-in 7 s
Position Reference Point	Support e Support Z
Servo Control	Pulse stri
Frequency Division Output	Encoderp
Speed/position Mode	Support te
Encoder	Support 5 Maximum

Friendly Human Machine Interface

(1) High Performance Keypad The standard LED keypad supports parameters loading and unloading with Max. length of 200m and digital potentiometer. The optional external LCD keypad supports parameters loading and unloading with displaying 10 lines and 1

The optional external LCD keypad supports parameters loading and unloading with displaying 10 lines and 10 rows of Chinese characters and several languages



•

 \oplus

 \oplus





on

- \sim 10V/0 \sim 20mA, -10V \sim +10V, differential pulse,
- cation and Multi-step Speed
- scale divisions and 4 zero positions
- externally-connected zero-position detection switch positioning Z-phase positioning of the encoder
- ing positioning:Position control at any position
- pulse frequency division output
- erminal switching
- 5V,12V and 24V increment ABZ encoder
- n frequency<300kHz

(2) PC Software

The software carries out tracking and fault location with the function of oscilloscope, making more convenient debugging and programming and facilitaion the current monitoring, back analysis and engineering management.





Connection Diagrams

Analog speed control and positioning control connection diagram

- Speed control: The speed of the spindle servo motor can be adjusted smoothly, stably and accurately via the host or analog voltage command given by the user (-10V~+10V or 0~10V)
- Positioning function: Select the positioning point through the combination of positioning terminals and start the positioning process via "spindle positioning/return to zero".

Pulse string positioning connection diagram

The position and speed of the spindle can be controlled accurately by pulse and direction command or 2-phase orthogonal pulse command which send by CNC system. It has identical function with the general servo driver.





Note: Pulse given and encoder frequency division output are not available for A1/B1 but available for H1.

Note: Pulse given and encoder frequency division output are not available for A1/B1 but available for H1.

-← ●

